Basic Laplace Theory

- Laplace Integral
- A Basic LaPlace Table
- A LaPlace Table for Daily Use
- Some Transform Rules
- Lerch's Cancelation Law and the Fundamental Theorem of Calculus
- Illustration in Calculus Notation
- ullet Illustration Translated to Laplace $oldsymbol{L}$ -notation

Laplace Integral

The integral

$$\int_0^\infty g(t)e^{-st}dt$$

is called the **Laplace integral** of the function g(t). It is defined by

$$\int_0^\infty g(t)e^{-st}dt \equiv \lim_{N o\infty}\int_0^N g(t)e^{-st}dt$$

and it depends on variable s. The ideas will be illustrated for g(t)=1, g(t)=t and $g(t)=t^2$. Results appear in Table 1 infra.

A Basic LaPlace Table

$$\begin{split} \int_0^\infty (1)e^{-st}dt &= -(1/s)e^{-st}|_{t=0}^{t=\infty} & \text{Laplace integral of } g(t) = 1. \\ &= 1/s & \text{Assumed } s > 0. \\ \int_0^\infty (t)e^{-st}dt &= \int_0^\infty -\frac{d}{ds}(e^{-st})dt & \text{Laplace integral of } g(t) = t. \\ &= -\frac{d}{ds}\int_0^\infty (1)e^{-st}dt & \text{Use} \\ &\int \frac{d}{ds}F(t,s)dt = \frac{d}{ds}\int F(t,s)dt. \\ &= -\frac{d}{ds}(1/s) & \text{Use } L(1) = 1/s. \\ &= 1/s^2 & \text{Differentiate.} \\ \int_0^\infty (t^2)e^{-st}dt &= \int_0^\infty -\frac{d}{ds}(te^{-st})dt & \text{Laplace integral of } g(t) = t^2. \\ &= -\frac{d}{ds}\int_0^\infty (t)e^{-st}dt &= -\frac{d}{ds}(1/s^2) & \text{Use } L(t) = 1/s^2. \\ &= 2/s^3 & \text{Use } L(t) = 1/s^2. \end{split}$$

Summary

Table 1. Laplace integral $\int_0^\infty g(t)e^{-st}dt$ for g(t)=1,t and t^2 .

$$\int_0^\infty (1) e^{-st} \, dt = rac{1}{s}, \qquad \int_0^\infty (t) e^{-st} \, dt = rac{1}{s^2}, \qquad \int_0^\infty (t^2) e^{-st} \, dt = rac{2}{s^3}.$$

In summary, $L(t^n)=rac{n!}{s^{1+n}}$

A Laplace Table for Daily Use

Solving differential equations by Laplace methods requires keeping a smallest table of Laplace integrals available, usually memorized. The last three entries will be verified later.

Table 2. A minimal Laplace integral table with L-notation

$$\int_0^\infty (t^n)e^{-st} dt = \frac{n!}{s^{1+n}}$$

$$\int_0^\infty (e^{at})e^{-st} dt = \frac{1}{s-a}$$

$$\int_0^\infty (\cos bt)e^{-st} dt = \frac{s}{s^2 + b^2}$$

$$\int_0^\infty (\sin bt)e^{-st} dt = \frac{b}{s^2 + b^2}$$

$$L(t^n) = \frac{n!}{s^{1+n}}$$

$$L(e^{at}) = \frac{1}{s-a}$$

$$L(\cos bt) = \frac{s}{s^2 + b^2}$$

$$L(\sin bt) = \frac{b}{s^2 + b^2}$$

Laplace Integral

The Laplace integral or the direct Laplace transform of a function f(t) defined for $0 \le t < \infty$ is the ordinary calculus integration problem

$$\int_0^\infty f(t)e^{-st}dt.$$

The Laplace integrator is $dx = e^{-st}dt$ instead of the usual dt.

A Laplace integral is succinctly denoted in science and engineering literature by the symbol

which abbreviates

$$\int_E (f(t)) dx$$

with set $E=[0,\infty)$ and Laplace integrator $dx=e^{-st}dt$.

Some Transform Rules

$$L(f(t) + g(t)) = L(f(t)) + L(g(t))$$

$$L(cf(t)) = cL(f(t))$$

$$L(y'(t)) = sL(y(t)) - y(0)$$

The integral of a sum is the sum of the integrals.

Constants c pass through the integral sign.

The t-derivative rule, or integration by parts.

Lerch's Cancelation Law and the Fundamental Theorem of Calculus

$$L(y(t)) = L(f(t))$$
 implies $y(t) = f(t)$ Lerch's cancelation law.

Lerch's cancelation law in integral form is

(1)
$$\int_0^\infty y(t)e^{-st}dt = \int_0^\infty f(t)e^{-st}dt \quad \text{implies} \quad y(t) = f(t).$$

Quadrature Methods

Lerch's Theorem is used *last* in Laplace's quadrature method. In Newton calculus, the quadrature method uses the Fundamental Theorem of Calculus *first*. The two theorems have a similar use, to *isolate* the solution y of the differential equation.

An illustration _____

Laplace's method will be applied to solve the initial value problem

$$y' = -1, \quad y(0) = 0.$$

Table 3. Laplace method details for y' = -1, y(0) = 0.

$$y'(t)e^{-st}dt=-e^{-st}dt$$
 Multiply $y'=-1$ by $e^{-st}dt$. Integrate $t=0$ to $t=\infty$. $\int_0^\infty y'(t)e^{-st}dt=-1/s$ Use Table 1. $s\int_0^\infty y(t)e^{-st}dt-y(0)=-1/s$ Integrate by parts on the left. $\int_0^\infty y(t)e^{-st}dt=-1/s^2$ Use $y(0)=0$ and divide. $\int_0^\infty y(t)e^{-st}dt=\int_0^\infty (-t)e^{-st}dt$ Use Table 1. $y(t)=-t$ Apply Lerch's cancelation law.

Translation to L-notation

Table 4. Laplace method L-notation details for $y'=-1,\,y(0)=0$ translated from Table 3.

$$L(y'(t))=L(-1)$$
 Apply L across $y'=-1$, or multiply $y'=-1$ by $e^{-st}dt$, integrate $t=0$ to $t=\infty$. Use Table 1 forwards.

$$sL(y(t))-y(0)=-1/s$$
 Integrate by parts on the left.

$$L(y(t)) = -1/s^2$$
 Use $y(0) = 0$ and divide.

$$L(y(t)) = L(-t)$$
 Apply Table 1 backwards.

$$y(t) = -t$$
 Invoke Lerch's cancelation law.

1 Example (Laplace method) Solve by Laplace's method the initial value problem y'=5-2t, y(0)=1 to obtain $y(t)=1+5t-t^2$.

Solution: Laplace's method is outlined in Tables 3 and 4. The L-notation of Table 4 will be used to find the solution $y(t) = 1 + 5t - t^2$.

$$L(y'(t)) = L(5-2t)$$
 Apply L across $y' = 5-2t$.
 $= 5L(1) - 2L(t)$ Linearity of the transform.
 $= \frac{5}{s} - \frac{2}{s^2}$ Use Table 1 forwards.
 $sL(y(t)) - y(0) = \frac{5}{s} - \frac{2}{s^2}$ Apply the t -derivative rule.

$$L(y(t)) = rac{1}{\epsilon} + rac{5}{\epsilon^2} - rac{2}{\epsilon^3}$$
 Use $y(0) = 1$ and divide.

$$L(y(t))=L(1)+5L(t)-L(t^2)$$
 Use Table 1 backwards.
$$=L(1+5t-t^2)$$
 Linearity of the transform.

$$y(t) = 1 + 5t - t^2$$
 Invoke Lerch's cancelation law.

2 Example (Laplace method) Solve by Laplace's method the initial value problem y'' = 10, y(0) = y'(0) = 0 to obtain $y(t) = 5t^2$.

Solution: The L-notation of Table 4 will be used to find the solution $y(t)=5t^2$.

$$L(y''(t)) = L(10) \qquad \text{Apply L across $y'' = 10$.}$$

$$sL(y'(t)) - y'(0) = L(10) \qquad \text{Apply the t-derivative rule to y'.}$$

$$s[sL(y(t)) - y(0)] - y'(0) = L(10) \qquad \text{Repeat the t-derivative rule, on y.}$$

$$s^2L(y(t)) = 10L(1) \qquad \text{Use $y(0) = y'(0) = 0$.}$$

$$L(y(t)) = \frac{10}{s^3} \qquad \text{Use Table 1 forwards. Then divide.}$$

$$L(y(t)) = L(5t^2) \qquad \text{Use Table 1 backwards.}$$

$$y(t) = 5t^2 \qquad \text{Invoke Lerch's cancelation law.}$$