

# Math 2280 - Lecture 38

Dylan Zwick

Fall 2013

In the last lecture I introduced the idea of a Fourier series, and we learned how to calculate a Fourier series for a function with period  $2\pi$ . Of course, not all periodic functions have period  $2\pi$ , so you may very well ask what we can do, if anything, with arbitrary periodic functions. In today's lecture we'll show that we can generalize our Fourier series formula from functions with period  $2\pi$  to functions with arbitrary period. Note this lecture is a little shorter than usual.

Today's lecture corresponds with section 9.2 from the textbook. The assigned problems for this section are:

Section 9.2 - 1, 9, 15, 17, 20

## General Fourier Series and Convergence

Suppose we have a function  $f(t)$  with period  $2L$ , where  $L > 0$ . If we define:

$$g(u) = f\left(\frac{Lu}{\pi}\right),$$

we see  $g(u)$  is  $2\pi$  periodic. So, the Fourier series, as defined in the last lecture, for  $g(u)$  is:

$$g(u) \sim \frac{a_0}{2} + \sum_{n=1}^{\infty} (a_n \cos(nu) + b_n \sin(nu)).$$

The coefficients are:

$$a_n = \frac{1}{\pi} \int_{-\pi}^{\pi} g(u) \cos(nu) du,$$

$$b_n = \frac{1}{\pi} \int_{-\pi}^{\pi} g(u) \sin(nu) du.$$

We note that  $t = \frac{Lu}{\pi}$ , and so  $f(t) = g\left(\frac{\pi t}{L}\right)$ . From this, we get the corresponding “Fourier series”<sup>1</sup> for  $f(t)$ :

$$f(t) \sim \frac{a_0}{2} + \sum_{n=1}^{\infty} \left( a_n \cos\left(\frac{n\pi t}{L}\right) + b_n \sin\left(\frac{n\pi t}{L}\right) \right),$$

where

$$a_n = \frac{1}{L} \int_{-L}^L f(t) \cos\left(\frac{n\pi t}{L}\right) dt$$

$$b_n = \frac{1}{L} \int_{-L}^L f(t) \sin\left(\frac{n\pi t}{L}\right) dt.$$

So, this generalizes the concept of a Fourier series to functions of period  $2L$ , where  $L$  is any positive number, and not restricted to  $\pi$ . We note that taking the above integrals from  $-L$  to  $L$  is, given the  $2L$ -periodicity of the function, completely arbitrary, and we could integrate instead over *any* connected interval of length  $2L$ .

---

<sup>1</sup>In quotations because, really, this isn’t so much a derivation as a motivation for a definition.

## Convergence of Fourier Series

We've defined the Fourier series of a function, but what does this Fourier series have to do with the original function? This question is answered by the next theorem.

**The Convergence Theorem** - Suppose that the periodic function  $f(t)$  is piecewise smooth. Then its Fourier series converges to:

1. the value  $f(t)$  at each point where  $f$  is continuous
2. the value  $\frac{1}{2}[f(t^+) + f(t^-)]$  at each point where  $f(t)$  is discontinuous.<sup>2</sup>

*Example* - Find the Fourier series of a square wave function with period 4:

$$f(t) = \begin{cases} -1 & -2 < t < 0 \\ 1 & 0 < t < 2 \\ 0 & t = \{-2, 0\} \end{cases}$$

---

<sup>2</sup>Note that  $f(t^+)$  means the limit of  $f$  as its argument approaches  $t$  "from the right", while  $f(t^-)$  means the limit of  $f$  as its argument approaches  $t$  "from the left".

More room for the example problem.

## Notes on Homework Problems

Problems 9.2.1 and 9.2.9 involve finding a Fourier series for a specified periodic function. Very similar to the example problem above.

Problems 9.2.15 and 9.2.17 require a little work (mostly algebra) but they're some of my favorite problems we do all semester, because they let us derive really neat relations. Kind of like the one at the end of the example problem above.

On problem 9.2.20 please remember that the function is  $2\pi$ -periodic. This is a frequent source of confusion on this problem.